

Type codes IndraDyn A

6.7 Type code MAF100

© Bosch Rexroth AG 2006

ZN-40002-100_NOR_N_EN_2010-07-30 fh11

Abbrev.	Column	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6	7	8	9	0	1	2	3	4	5	6	7	8	9	0	
Example:		M	A	F	1	0	0	C	-	0	1	5	0	-	F	Q	-	S	0	-	A	P	0	-	0	5	-	N	1													

Product
MAF = MAF

Size
100 = 100

Length
Lengths = B, C, D

Winding
MAF100B = 0050, 0100, 0150, 0200, 0250
MAF100C = 0050, 0100, 0150, 0200, 0250
MAF100D = 0050, 0100, 0150, 0200, 0250

Cooling
Liquid cooling with connection thread 1/4" = FQ
Liquid cooling with
Enclosed rapid action coupling 1/4" = FR

Encoder 1
Singleturn absolute encoder, EnDat2.1, 2048 increments = S2
Singleturn absolute encoder, EnDat2.1,
2048 increments, for Ex areas = S6
Multiturn absolute encoder, EndDat2.1, 2048 increments = M2
Multiturn absolute encoder, EndDat2.1,
2048 increments, for Ex areas = M6
Incremental encoder, 2048 increments = C0
without motor encoder = N0

Fig. 6-12: Type code MAF100 (1/2)

Fig. 6-13: Type code MAF100 (2/2)